



### Main

|                                    |   |
|------------------------------------|---|
| Range                              | Lineryg   |
| Product name                       | Lineryg TR                                      |
| Product or component type          | Vertical bridge                                 |
| Device short name                  | TRA   |
| Accessory / separate part category | Connection accessory                            |
| Product compatibility              | TRV screw terminal - passthrough terminal block |

### Complementary

|                             |                         |
|-----------------------------|-------------------------|
| Cable cross section         | 2.5...4 mm <sup>2</sup> |
| Number of connections       | 2                       |
| Number of measurement input | 4                       |
| Quantity per set            | Set of 50               |
| Net weight                  | 1.1 g                   |

### Packing Units

|                  |          |
|------------------|----------|
| Package 1 Weight | 0.001 kg |
| Package 1 Height | 0.500 dm |
| Package 1 width  | 1.500 dm |
| Package 1 Length | 1.700 dm |

### Offer Sustainability

|                             |  |
|-----------------------------|--|
| Sustainable offer status    | Green Premium product  |
| REACH Regulation            | <a href="#">REACH Declaration</a>  |
| REACH free of SVHC          | Yes  |
| EU RoHS Directive           | Pro-active compliance (Product out of EU RoHS legal scope) <a href="#">EU RoHS Declaration</a> |
| Toxic heavy metal free      | Yes  |
| Mercury free                | Yes  |
| RoHS exemption information  | <a href="#">Yes</a>  |
| China RoHS Regulation       | <a href="#">China RoHS Declaration</a>   |
| Environmental Disclosure    | <a href="#">Product Environmental Profile</a>  |
| Halogen content performance | Halogen free plastic parts product   |

### Contractual warranty

|          |           |
|----------|-----------|
| Warranty | 18 months |
|----------|-----------|

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.