



### Main

Range	Masterpact
Product or component type	Connection adapter
Device application	Communication
Range compatibility	Masterpact MTZ1 circuit breaker

### Complementary

Mounting mode	Fixed
Mounting support	Chassis
Localisation on device	Behind control unit
Maximum supply current	0.8 A
Power consumption in W	14 W
Provided equipment	1 instruction sheet
Offer type	Spare part

### Packing Units

Package 1 Weight	1.000 kg
Package 1 Height	1.000 dm
Package 1 width	1.000 dm
Package 1 Length	1.000 dm

### Offer Sustainability

REACH Regulation	<a href="#">REACH Declaration</a>
REACH free of SVHC	Yes
EU RoHS Directive	Compliant <a href="#">EU RoHS Declaration</a>
Toxic heavy metal free	Yes
Mercury free	Yes
RoHS exemption information	<a href="#">Yes</a>
China RoHS Regulation	<a href="#">China RoHS Declaration</a>

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.