



Main

Product or component type	Interphase barrier
Range compatibility	<p>Masterpact NW Masterpact NW08 circuit-breaker  Masterpact NW Masterpact NW10 circuit-breaker  Masterpact NW Masterpact NW12 circuit-breaker  Masterpact NW Masterpact NW16 circuit-breaker  Masterpact NW Masterpact NW20 circuit-breaker  Masterpact NW Masterpact NW25 circuit-breaker  Masterpact NW Masterpact NW32 circuit-breaker  Masterpact NW Masterpact NW40 circuit-breaker  Masterpact NW Masterpact NW08 switch disconnecter  Masterpact NW Masterpact NW10 switch disconnecter  Masterpact NW Masterpact NW12 switch disconnecter  Masterpact NW Masterpact NW16 switch disconnecter  Masterpact NW Masterpact NW20 switch disconnecter  Masterpact NW Masterpact NW25 switch disconnecter  Masterpact NW Masterpact NW32 switch disconnecter  Masterpact NW Masterpact NW40 switch disconnecter  Masterpact NW Masterpact NW08 1000V circuit-breaker  Masterpact NW Masterpact NW10 1000V circuit-breaker  Masterpact NW Masterpact NW12 1000V circuit-breaker  Masterpact NW Masterpact NW16 1000V circuit-breaker  Masterpact NW Masterpact NW20 1000V circuit-breaker  Masterpact NW Masterpact NW25 1000V circuit-breaker  Masterpact NW Masterpact NW32 1000V circuit-breaker  Masterpact NW Masterpact NW40 1000V circuit-breaker  Masterpact NW Masterpact NW08 1000V switch disconnecter  Masterpact NW Masterpact NW10 1000V switch disconnecter  Masterpact NW Masterpact NW12 1000V switch disconnecter  Masterpact NW Masterpact NW16 1000V switch disconnecter  Masterpact NW Masterpact NW20 1000V switch disconnecter  Masterpact NW Masterpact NW25 1000V switch disconnecter  Masterpact NW Masterpact NW32 1000V switch disconnecter  Masterpact NW Masterpact NW40 1000V switch disconnecter</p>
Accessory / separate part type	Insulation accessories
Poles description	3P 4P
Quantity per set	Set of 3

The information provided in this documentation contains general descriptions and/or technical characteristics of the performance of the products contained herein. This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither Schneider Electric Industries SAS nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.

## Complementary

Mounting mode	Drawout
---------------	---------

## Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Weight	1.03 kg
Package 1 Height	5.5 cm
Package 1 width	25.5 cm
Package 1 Length	38 cm
Unit Type of Package 2	S04
Number of Units in Package 2	8
Package 2 Weight	9.514 kg
Package 2 Height	30 cm
Package 2 width	40 cm
Package 2 Length	60 cm
Unit Type of Package 3	P12
Number of Units in Package 3	32
Package 3 Weight	70 kg
Package 3 Height	45 cm
Package 3 width	80 cm
Package 3 Length	120 cm

## Offer Sustainability

REACH Regulation	<a href="#">REACH Declaration</a>
REACH free of SVHC	Yes
EU RoHS Directive	Pro-active compliance (Product out of EU RoHS legal scope) <a href="#">EU RoHS Declaration</a>
Toxic heavy metal free	Yes
Mercury free	Yes
RoHS exemption information	<a href="#">Yes</a>
China RoHS Regulation	<a href="#">China RoHS Declaration</a>

## Contractual warranty

Warranty	18 months
----------	-----------